

European Table of Frequency

Series	Frequency Range	Max Power	License	Countries																											
				I	FR	D	AT	BE	GB	GR	NL	IR	ES	PT	EE	SV	NO	LT	TK	CZ	DK	HU	PL	FI	LI	RU	CH	RO	SK	CY	
WM100	185.150 - 211.250	10 mW	Required *	L	F	F	L	L	L	L	F	L	L	L	L	F	F	L	F	F	F	L	F	F	L	L	L	L	L	L	L
WM101 V2	863 - 865 Mhz	10 mW	Free	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F
WM300	823 - 832 MHz	10 mW	Required *	L	F	F	L	X	L	L	X	X	L	X	F	F	L	L	X	F	F	F	F	F	X	X	L	L	L	L	
WM700	823 - 832 MHz	10 mW	Required *	L	F	F	L	X	L	L	X	X	L	X	F	F	L	L	X	F	F	F	F	F	X	X	L	L	L	L	
WM700 A	512 – 562 MHz	10 mW	Required *	L	F	L	L	L	L	L	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
RMW921	823-832 / 863-865 MHz	10/20 mW	Required *	L	F	F	L	X	L	L	X	X	L	L*	F	F	L	L	X	F	F	F	F	F	X	X	L	L	L	L	
RMW921 A	551 – 581 MHz	10/20 mW	Required *	L	F	L	L	L	L	L	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
RM3000EK	863 - 865 Mhz	10 mW	Free	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	
RM3000EKA	673-697.8 Mhz	10 mW	Required *	L	F	L	L	L	L	F	F	X	F	F	X	L	F	L	F	L	F	F	F	F	L	F	F	F	F	L	
EKJJ	863 - 865 Mhz	10 mW	Free	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	
EKJJA	512 – 541,7 MHz	10 mW	Required *	L	F	L	L	L	L	L	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
EKJM	863 - 865 Mhz	10 mW	Free	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	
EKJMA	512 – 541,7 MHz	10 mW	Required *	L	F	L	L	L	L	F	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
UXLR	863 - 865 Mhz	10 mW	Free	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	
UXLR	568 – 581 MHz	10 mW	Required *	L	F	L	L	L	L	L	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
AETHERRM1 A	514 – 542 Mhz	10 mW	Required *	L	F	L	L	L	L	L	F	X	L	L	X	L	L	L	F	L	F	F	F	F	L	F	F	L	L	L	
AETHERRM1 B	606 – 614 Mhz	10 mW	Required *	L	F	L	L	L	L	F	F	X	F	F	X	L	F	L	F	L	F	F	F	F	L	F	F	F	F	L	
AETHERRM1 C	655 – 679 Mhz	10 mW	Required *	L	F	L	L	L	L	F	F	X	F	F	X	L	F	L	F	L	F	F	F	F	L	F	F	F	F	L	
AETHERRM1 D	823-832 / 863-865 MHz	10 mW	Required *	L	F	F	L	X	L	L	X	X	L	L*	F	F	L	L	X	F	F	F	F	F	X	X	L	L	L	L	

*
F: Free
L: License required
L*: 823-832 Not available
X: Not available