



FREE5LT

ALL-IN-ONE BATTERY POWERED SOUND SYSTEM



PROEL FREE systems gives you the freedom to play your music or amplify your voice anywhere without worrying about where to plug the power cord, how to connect your MP3 player or how to set your microphone.

FREE5LT is battery powered combo sound systems with a full set of features and the sound you don't expect from this kind of products. It includes a versatile MP3 player with USB port and BLUETOOTH connection, featuring a large LCD and a full control set.

FREE5LT is hosted in a compact and road-proof plastic cabinet that provides maximum portability and protection, allowing the systems to be taken everywhere. It is also fitted with an adapter for standard microphone stand. Equipped with a 5" full band speaker and a 20W power amplifier, FREE5LT is an all-in-one multi-purpose mobile system for indoor and outdoor applications requiring high quality sound and advanced features.

The WIRELESS module included provides a clean and hassle-free wireless connection with the included handheld microphones for the maximum freedom of movement.

The Li-ion internal rechargeable battery provides up to 4-5 hours of mains-free continuous operation.







KEY FEATURES

- · All-in-one battery powered sound system
- License-free UHF wireless module (863-865 MHz) with handheld microphone
 - Built-in MP3 player with USB port and BLUETOOTH audio connection,

LCD display and IR remote control, REC function

- 1 MIC + 1 STEREO LINE inputs, 1 LINE output
 - 20W built-in Class D amplifier
 - 5" full-range speaker
 - Built-in alarm siren
 - LED flashlight
- Rechargeable Li-ion battery with 10-16 hours stand-by time
- · Compact and light-weight PP cabinet with one handle, shoulder strap and microphone stand adapter
 - Padded carrying bag included



TECHNICAL SPECIFICATION

| MONO inputs | 1 x MIC IN (JACK) |
|-------------------------|--|
| STEREO inputs | 1 x MIC IN (JACK) 1 x LINE IN (mini JACK) |
| Outputs | LINE OUT (mini JACK) |
| <u>'</u> | |
| Extra features | Built-in alarm siren, built-in LED torch |
| WIRELESS Section | 0.45 |
| Wireless Receiver | Built-in |
| Handheld Transmitter | FR4H |
| Bodypack Transmitter | FR4B (optional) |
| Headset Microphone | HS2 (optional) |
| Modulation Mode | FM |
| Frequency Range | UHF 863 – 865 MHz |
| Audio bandwidth | 60 Hz – 16 KHz |
| S/N Ratio | > 100 dB |
| HANDHELD RF output | < 10 mW |
| BODYPACK RF output | < 10 mW |
| THD | < 0.1% |
| MULTIMEDIA Section | |
| Player Type | USB / BLUETOOTH player with REC function |
| Compatible File Formats | WAV, MP3, WMA |
| Control Interface | LCD display, REMOTE control |
| AMPLIFIER Section | |
| Continuous Power | 10 W (w/battery) 20 W (w/AC) |
| LOUDSPEAKER Section | · |
| Loudspeaker System | Full-range system |
| Device | 5" full-range speaker |
| Frequency Response | 120Hz - 18KHz, -3dB |
| Construction | Polypropylene Cabinet, Metal Grille |
| Handles | 1 top |
| Pole Holder | 1 microphone stand adapter bottom |
| GENERAL Specifications | |
| Dimensions (W x H x D) | 13.5x15x24.5 |
| Weight | 1.5 Kg (3.3 lb) |
| Recharge Battery | 1 x 11.1V / 1.5Ah Li-lon |
| Battery Recharging Time | 2 hours |
| Battery Working Time | 4-5 hours |
| Battery Standby Time | 10-16 hours |
| Power Supply | AC 90-264V~ 50/60Hz adapter |



