

QUIVER DMX CONTROLLER



QUIVER is Sagitter's new lighting console, characterised by an innovative design and dedicated to the control of all the conventional and automated lighting fixtures required by any lighting designer, and ideal for managing a wide variety of lighting shows.

Its innovative operating system provides an intuitive graphical interface intended also for those semi-professionals who need a flexible and more powerful operating system than traditional consoles commonly used in the market.

The console's heart relies on a large 7-inch high luminosity touch-screen LCD with full color display designed for an enhanced user experience. Its intuitive architectural graphical structure display provides an instant-access lighting controller bank without any external hardware or monitor devices.

All main editing functions are assignable to a new generation four-touch fader that ensures fast and dynamic control of all the functions displayed on the LCD screen.

The unique touch fader section was designed in order to allow simultaneous and immediate manual control of multiple parameters. Moreover, the simplified editing program function allows fast handling of all live show activities.

All the remaining moving parameters such as PAN and TILT are quickly controlled by an accurate joystick which provides user-customized control of the fine parameters ranging from 8/12 and 16 bit, and optional Lock function for accurate work of art.

The console section is dedicated to live, conceived to allow the creation of any live shows, and features:

- 6 configurable faders (playback, master group, manual cue)
- 6 fully customized keys (playback)
- 12 keys for immediate playback registers control

For the most discerning users QUIVER offers the unique possibility to increase its live block with two additional expansion modules, powering the console up to 1536 channels divided into three separate DMX universes.



TECHNICAL SPECIFICATION

Controls	Colour Display touch-screen TFT LCD 7"
	6 configurable slider as playback, master group or manual Cue
	6 configurable key as play, flash
	12 keys for direct access to playback
	4 touch-fader for the control of the attributes during the programming and control of the effects and during playback and manual use
	Joystick for PAN and TILT movement control with lock and fine keys
Description	Effective graphic interface able to easily manage programming and playback for a maximum of 144 cue-list organize in 12 pages each having a maximum of 999 cues
	512 channel for each single universe DMX for the control of dimmer and/or intelligent projector, available simultaneously on XLR connector 3 poles
	Up to 1536 channel with Quiver Expand
	Up to 36 Cue-list run concurrently (with 2 Expand connected)
	"Shape engine" customizable and applicable to different functions
	Up to 6 different families of "palettes" programmable for a flexible and easy control of intelligent projectors
	Up to 999 Cues for each playback
	Library "personalities" upgradeable, creating fixture via software for PC
	"Palettes" Chris/Gam/Lee and Rosco pre-program usable on all machines with mixing colors RGB or CMY
	Maximum Number of storable cues to show: 999
	RDM ready (Prepared for enlargement of technology)
	Wireless ready (Designed for the insertion of a wireless transmitter sold separately)
	External Power Supply: 100-240V 50-60Hz
Connection	DMX out: 1x XLR 3 pins
	Expand: 2x RJ45 for expansions connection
	1 USB port for backup, lamp power supply and update the fixture
	Jack 6,3mm for connecting the pedals for controlling the gearbox scenes
Weight and Dimensions	Net weight: 3,4 kg
	Dimensions: 420x98x288 mm



QUIVERX


DMX CONTROLLER EXPANSION



The QUIVERX expansion block was designed to increase the number of physical controller keys. The Expand is equipped with six faders, six button flash keys, 12 keys for direct access to playback registers, and one DMX universe through 3-pole XLR connectors. The QUIVERX expander can be easily connected to the mother console without any additional software, thanks to its dedicated cable that allows up to two expanders per console.

TECHNICAL SPECIFICATION

Controls	6 configurable slider as playback, master group or manual Cue
	6 configurable key as play, flash
	12 keys for direct access to playback
Connection	DMX out: 1x XLR 3 pins
	Expand: 1x RJ45
Weight and Dimensions	Net weight: 1,4 kg
	Dimensions: 196x98x288 mm



QUIVER + 1 QUIVERX



QUIVER + 2 QUIVERX

